


IR-08-F

IMAGE REJECT MIXER



SPECIFICATIONS

Name:	IR-08-F
LO Frequency (+10 dBm):	80-160 MHz
RF Frequency (-10 dBm):	LO \pm IF (20 MHz)
LO Power:	10 dBm nom.
Conversion Loss:	8.5 dB max.
1 dB Compression Point:	+3 dBm min.
Image Rejection:	25 dBc min.
Connector Type:	Surface

PORT CONFIGURATION

LO:	12
RF:	6
IF1:	3
IF2:	9
Ground:	All Others

Image rejection minimum applies to IF1 when RF < LO frequency.
Image rejection minimum applies to IF2 when RF > LO frequency.

This is a commercial off the shelf (COTS) product.
For an equivalent product that meets DFARS materials compliance, contact sales.
All specifications are subject to change without notice at any time. Rev: 160203